


SWIT[®]

Model: **S-1221F**
21.5" Broadcast LCD Monitor



User Manual

Please read this User Manual
throughout before using.

Preface

Congratulations on your purchase of this product. Please read this user manual carefully.

1. All internal technologies of this product are protected, including device, software and trademark.
Reproduction in whole or in part without written permission is prohibited.
2. All brands and trademarks of SWIT Electronics Co., Ltd. are protected and other relative trademarks in this user manual are the property of their respective owners.
3. Due to constant effort of product development, SWIT reserves the right to make changes and improvements to the product described in this manual without prior notice.
4. The warranty period of this product is 2 years, and does not cover the following:
 - (1) Physical damage to the surface of the products, including scratches, cracks or other damage to the LCD screen or other externally exposed parts;
 - (2) Misuse, abuse or negligent operation to the product;
 - (3) The product is disassembled by anyone other than an authorized service center.It is considered normal that the LCD bright dot defects are not to exceed three.
5. For any suggestions and requirements on this product, please contact us through phone, fax, Email, etc.

SWIT Electronics Co., Ltd.

Address: 10 Hengtong Road, Nanjing Economic and Technological Development Zone,
Nanjing 210038, P.R.China

Phone: +86-25-85805753

Fax: +86-25-85805296

Email: contact@swit.cc

Website: <http://www.swit.cc>

Maintenance

- **The Monitor**

1. Please keep the signal terminals and the cooling vent away from knife-edge, metal or liquid in order to avoid short-circuit and damage.
2. Please don't try to disassemble any parts of the monitor by yourself, which would probably damage the monitor and do harm to human body, and it will cause the invalidation of product warranty.
3. Please don't touch the screen with your fingers, which would probably deface the screen.
4. Please don't press the screen; the LCD is extremely exquisite and flimsy.

- **The power**

Please use the power adapter provided or recommended by the manufacturer in order to avoid damage. For a third party power adapter, please make sure the voltage range, supplied power, and polarity of power lead are fit.

Please disconnect the power cable under the following situations:

1. If you do not operate this monitor for a period of time;
2. If the power cable or power adaptor is damaged;
3. If the monitor housing is broken.

- **Working Environment**

1. Please don't lay this product on the unstable place.
2. Please don't lay this product in hot, cold or wet location.

- **Cleaning**

1. Please clean the screen with dry and downy cloth or special LCD cleanser.
2. Please do not press hard when cleaning the screen.
3. Please do not use water or other chemical cleanser to clean the screen. The chemical may damage the LCD.

1. Features

◆ Full-HD 21.5" LCD Panel

1920×1080 resolution, 1000:1 contrast

◆ Multiple inputs

HD/SD-SDI, HDMI and Composite input

◆ Loop through outputs

Each of the 2 input HD/SD-SDI and HDMI has loop through output.

◆ SDI 1080psf supported

Support SMPTE-RP211 format: 1080psf (30 / 29.97 / 25 / 24 / 23.98)

◆ HDMI converted to SDI output

Supported HDMI formats: 480i / 576i / 720p (50, 59.94, 60) / 1080i (50, 59.94, 60) / 1080P (23.98 24, 25, 29.97, 30), and the output SDI will embed the audio (48KHz) from HDMI.

◆ Waveform (Y, Cb, Cr, R, G, B) and full scale

There are totally 6 kinds of waveform display, available under both SDI and HDMI, to check the Luminance (Y), Blue-difference (Cb), Red-difference (Cr), Red (R), Green (G), Blue (B), and the Y, Cb, Cr can be simultaneously displayed, R, G, B can be simultaneously displayed, and each of the waveforms can be set to full scale display.

◆ Vector scope

The displayed vector scope pattern is available under both SDI and HDMI, represents saturation as distance from the center of the circle, and hue as the angle, in standard position, around it.

◆ Histogram (R, G, B)

The histogram is a bar graph that shows the distribution of luminance values in the picture. There're R, G, B histograms that individually displayed simultaneously, available under both SDI and HDMI.

◆ 16-ch audio meter

Under HDSDI, it displays 16 channels audio bars, with mark, and under SDSDI or HDMI, it displays 2 channels audio bars with mark. The audio bar is green, and will turn yellow when audio exceeds -20dB, and turn red when exceeds -10dB.

◆ SDI timecode

Under SDI input, it can display the SMPTE timecode(VITC1, VITC2 or LTC), which is used extensively for synchronization, and for logging and identifying material in recorded media.

◆ Peaking focus assist (red/blue switch)

The Peaking focus assist function is to mark the sharpest edges of the image with red or blue color, for users to check if the subjects are focused.

◆ Zebra stripes

Zebra Stripes are used to check if the image is over exposed or not by showing black and white lines on the monitor. It is considered over exposed when luminance value exceeds 90%.

◆ False color

The false color is used to aid in the setting of camera exposure. Under false color mode, there's a color chart on the bottom of screen for reference. The over exposed subjects (above 101 IRE) on the monitor will display as RED, and the underexposed subjects will display as BLUE. For correct exposed subjects, it will display as green and pink.

◆ Blue Only

Under Blue Only Mode, only blue pixels are used to generate the image, because hue and saturation can be adjusted quicker and more accurately.

◆ User definable function keys

There are 3 function keys on the monitor front panel, which permit users to define shortcuts for the various functions.

◆ User editable video title

User can edit a video title for the current camera, and the title will display on the top of screen.

◆ Front and Rear 3-color TALLY light


1 front and 2 rear TALLY lights design, to give "live" signals to people in front of the camera, as well as the camera operator behind.

◆ Image Flip


Set image to rotate by 180°

2. Panel Instruction


Front view



- (1) **SPEAKER:** For SDI and HDMI embedded audio monitoring. (Will not work if earphone is plugged in)
- (2) **SOURCE:** Input signal selection, revolve the “ENTER” to select the input video signal.
- (3),(4),(5) **F1, F2, F3:** User definable function keys
- (6) **FOCUS:** Peaking Focus Assist
Press “FOCUS” once, it will display the current peaking on/off status. Press “FOCUS” again to switch on RED line focus assist, switch on BLUE line focus assist, and switch off in turn.
- (7) **WAVEFORM:** Display waveform
Press “WAVEFORM” once, it will display the waveform menu as:
Revolve “ENTER” to select a waveform display mode and turn it on.
The selected waveform will display on the screen.
- (8) **F.COLOR:** False color
Press “F.COLOR” once, it will display the current false color on/off status. Press “F.COLOR” again to switch on/off the false color mode.
- (9) **VECTOR:** Press “VECTOR” to switch on/off the Vector scope.
- (10) **DISPLAY:** Press “Display” to display safety mark, title and the current input signal information.
- (11) **MENU:** Press to enter Menu
- (12) **ENTER:** Select and Apply
Under menu system, revolve “ENTER” to adjust settings and press to apply; and out of menu system, directly revolve “ENTER” to adjust volume.
- (13) **BRIGHT:** Revolve “BRIGHT” to adjust brightness value from 0~100. Default value is 75.
- (14) **CONTRAST:** Revolve “CONTRAST” to adjust contrast value from 0~100. Default value is 50.
- (15) **SATURATION:** Revolve “SATURATION” to adjust saturation value from 0~100. Default value is 50.
- (16) **POWER:** Power on/off
Connect with power cable, press the “POWER” to switch on the monitor. Press again to switch off.
Disconnect with power cable if the monitor will not be used for a period of time.
- (17) **PHONE:** 3.5mm earphone socket, for SDI embedded audio, HDMI embedded audio monitoring.
- (18) **TALLY Light:** Red, Green and Yellow 3-color TALLY indicator



Rear view



- (1) **Battery mount:**
Gold mount / V-lock mount option
S-1221FA: Gold mount; S-1221FS: V-lock mount
- (2) **HDMI-IN:** HDMI input
- (3) **SDI-LOOP2:** HD/SD-SDI loop through output from SDI-IN2 (BNC connector)
- (4) **SDI-LOOP1:** HD/SD-SDI loop through output from SDI-IN1 (BNC connector)
- (5) **SDI OUT:** HDMI converted to SDI output (BNC connector)
- (6) **CVBS-IN:** Composite video input (BNC connector)
- (7) **SDI-IN1:** HD/SD-SDI input (BNC connector)
- (8) **SDI-IN2:** HD/SD-SDI input (BNC connector)
- (9) **HDMI-LOOP:** HDMI loop through output
- (10) **TALLY controlling port** (DB-9)
- (11) **DC 12V IN:** Connect with DC12V 4-pin XLR power adapter. (Pin 1: Negative, Pin 4: Positive)

Input formats

Input		Supported formats
CVBS		PAL / NTSC
HDMI		480i / 576i / 480P / 576P
		1080i (60 / 59.94 / 50)
		720p (60 / 59.94 / 50)
		1080p (60 / 59.94 / 50 / 30 / 29.97 / 25 / 24 / 23.98)
SDI	SMPTE-274M	1080i (60 / 59.94 / 50)
		1080p (30 / 29.97 / 25 / 24 / 23.98)
	SMPTE-RP211	1080psf (30 / 29.97 / 25 / 24 / 23.98)
	SMPTE-296M	720p (60 / 59.94 / 50)
	SMPTE-125M	480i (59.94)
ITU-R BT.656		576i (50)









3. Menu Operation

- (1) Press "MENU" and it will display menu system
- (2) Revolve "ENTER" to select an item. The selected item will be highlighted display.
- (3) Press "ENTER" to enter the selected item.
- (4) Under menu system, press "MENU" to back to previous menu.
*The menu will automatically save and quit if it remains idle.

3.1 PICTURE submenu

The PICTURE submenu includes:




- (1) **CONTRAST**: 0-100 value adjustment
- (2) **BRIGHTNESS**: 0-100 value adjustment
- (3) **HUE**: 0-100 value adjustment
(Only available under CVBS NTSC input)
- (4) **SATURATION**: 0-100 value adjustment
- (5) **SHARPNESS**: 0-100 value adjustment

PICTURE	
PICTURE	CONTRAST  50
SYSTEM	BRIGHTNESS  95
OSD	HUE  50
TITLE	SATURATION  50
DISPLAY	SHARPNESS  50
F KEY	
 : ADJ  : OK  : EXIT	

3.2 SYSTEM submenu

The SYSTEM submenu includes:







- (1) **RATIO**: Aspect ratio "16:9" / "4:3" selection
- (2) **SCAN**: "UNDERSCAN" / "OVERSCAN" selection
- (3) **ZOOM**: "OFF", "ZOOM1" and "ZOOM2" selection
- (4) **MARKER**: Select and set the safe area scale from 80%, 85%, 90% and 95%.
- (5) **FLIP**: Select "ON" to flip the picture by 180°.
- (6) **RESET**: Select "YES" to recover all to factory setting.

SYSTEM	
PICTURE	RATIO ◀ 16:9 ▶
SYSTEM	SCAN ◀ UNDERSCAN ▶
OSD	ZOOM ◀ OFF ▶
TITLE	MARKER ◀ 80% ▶
DISPLAY	FLIP ◀ OFF ▶
F KEY	RESET ◀ YES ▶
 : ADJ  : OK  : EXIT	

3.3 OSD submenu

The OSD submenu includes:

- (1) **LANGUAGE**: Menu language selection
- (2) **H-POSITION**: Menu horizontal position (0-100) adjustment, real-time preview and default value: 50.
- (3) **V-POSITION**: Menu vertical position (0-100) adjustment, real-time preview and default value: 50.
- (4) **DURATION**: Menu timeout setting (5-60)
Set a time (in seconds) in which the menu will automatically quit if remains idle. Default: 15.

OSD	
PICTURE	LANGUAGE ◀ ENGLISH ▶
SYSTEM	H-POSITION  50
OSD	V-POSITION  50
TITLE	DURATION  15
DISPLAY	
F KEY	
 : ADJ  : OK  : EXIT	

3.4 TITLE submenu

Revolve "ENTER" button to select the letters, and press "ENTER" to input. Select SPACE to input space and DEL to delete the left letter. Max 10 letters are supported. After setting, press "MENU", the system will save data to current user and quit menu. The menu will automatically save and quit if it remains idle.

PICTURE SYSTEM OSD TITLE DISPLAY F KEY	TITLE															
	0	1	2	3	4	5	6	7	8	9						
	A	B	C	D	E	F	G	H	I	J						
	K	L	M	N	O	P	Q	R	S	T						
	U	V	W	X	Y	Z	SPACE	DEL								
	TITLE: CAM 1															
:ADJ :OK :MENU :EXIT																

3.5 DISPLAY submenu

The DISPLAY submenu is to select the items to be displayed on screen when 'DISPLAY' button is pressed. Revolve "ENTER" to turn on/off the items:

- (1) **INFO:** Including Input format, aspect ratio, underscan/overscan, zoom status
- (2) **MARKER:** Safe area
- (3) **TITLE:** User edited title
- (4) **MARKER4:3:** The 4:3 scale mark on 16:9 image. (Only available under HD input)

PICTURE SYSTEM OSD TITLE DISPLAY F KEY	DISPLAY			
	INFO.	◀	ON	▶
	MARKER	◀	ON	▶
	TITLE	◀	ON	▶
	MARKER 4:3	◀	ON	▶
:ADJ :OK :MENU :EXIT				

3.6 F KEY submenu


The F KEY Settings Submenu is to define Function Key F1, F2 and F3. The available function items are:

- 01- **RATIO:** Aspect ratio 16:9 / 4:3 switch
- 02- **SCAN:** Underscan / Overscan switch
- 03- **ZOOM:** Picture Zoom-in
- 04- **B/W:** Color / Black & white switch
- 05- **BLUE ONLY:** Blue only mode switch on/off
- 06- **ZEBRA:** Zebra over exposure switch on/off
- 07- **VECTOR:** Vector scope switch on/off
- 08- **PATTERN:** Internal colorbar switch on/off
- 09- **RGB HIST:** R, G, B Histogram switch on/off
- 10- **TIMECODE:** SDI timecode display switch on/off
- 11- **F.COLOR:** False color mode switch on/off
- 12- **AUDIO BAR:** Audio meter display switch on/off
- 13- **FOCUS:** Peaking focus assist switch on/off,
- 14- **FLIP:** Image flip

PICTURE SYSTEM OSD TITLE DISPLAY F KEY	F KEY			
	F1 KEY	◀	01-RATIO	▶
	F2 KEY	◀	02-SCAN	▶
	F3 KEY	◀	03-ZOOM	▶
:ADJ :OK :MENU :EXIT				

4. TALLY Light Operation

There are front and rear TALLY lights on the monitor, which can display RED, GREEN and YELLOW signals. The TALLY light controlling port is the DB-9 socket at the rear panel, and terminal description is as follows:



Terminal	1	2	3	4	5	6	7	8	9
Description		Y	G	R			GND	GND	GND

The RED light is on when connecting the terminal “R” with “GND”, and goes out when disconnecting.

The GREEN light is on when connecting the terminal “G” with “GND”, and goes out when disconnecting.

The YELLOW light is on when connecting the terminal “Y” with “GND”, and goes out when disconnecting.

5. Specifications

LCD Performance		
Size		21.5 inches
Display area		477×268mm
Resolution		1920×RGB×1080
Aspect ratio		16:9 (4:3 adjustable)
Brightness		250cd/m ²
Contrast		1000:1
Color		16.77 million colors
Viewing angle		Horizontal: 170° Vertical: 170°
Video Format		
CVBS		NTSC / PAL
SDI	SMPTE-274M	1080i (60 / 59.94 / 50)
		1080p (30 / 29.97 / 25 / 24 / 23.98)
	SMPTE-RP211	1080psf (30 / 29.97 / 25 / 24 / 23.98)
	SMPTE-296M	720p (60 / 59.94 / 50)
	SMPTE-125M	480i (59.94)
	ITU-R BT.656	576i (50)
HDMI		480I / 576I / 480P / 576P
		1080i (60 / 59.94 / 50)
		720p (60 / 59.94 / 50)
		1080p (60 / 59.94 / 50 / 30 / 29.97 / 25 / 24 / 23.98)
General		
Working voltage		DC / battery 11V-17V
Power consumption		≤39W
Working temperature		0℃～+40℃
Working humidity		10%～90%
Storage temperature		- 15℃～ + 60℃
Storage humidity		10%～90%
Dimensions		522×432×165mm
Net weight		7800g

6. Packing List

Monitor	× 1
User manual	× 1
Power adaptor	× 1
Power cable	× 1
Desktop bracket	× 1

SWIT®